

Q : How to set the Multiple AP function of N.MINI?

A :

Please login the web management of N.MINI, and get into the page of Multiple AP function.

Multiple APs

This page shows and updates the wireless setting for multiple APs.

No.	Enable	Band	SSID	Data Rate	Broadcast SSID	WMM	Access	Active Client List
AP1	<input checked="" type="checkbox"/>	2.4 GHz (B+G+N)	mini2	Auto	Enabled	Enabled	WAN	Show
AP2	<input type="checkbox"/>	2.4 GHz (B+G+N)	airlive2	Auto	Enabled	Enabled	LAN+WAN	Show
AP3	<input type="checkbox"/>	2.4 GHz (B+G+N)	airlive3	Auto	Enabled	Enabled	LAN+WAN	Show
AP4	<input type="checkbox"/>	2.4 GHz (B+G+N)	airlive4	Auto	Enabled	Enabled	LAN+WAN	Show

Function	Description
Enable	Enable/disable the multiple APs
Band	This function will be available under 2.4GHz (B/G/N) mode.
SSID	A SSID is referred to a network name because essentially it is a name that identifies a wireless network.
Data Rate	There are several data rate that you can select from the pull-down menu.
Broadcast SSID	<p>Enabled: This Wireless Router will show its network name (SSID) to stations.</p> <p>Disabled: This Wireless Router will hide the network name to stations. If stations want to connect to this Wireless Router, this Router's network name(SSID) should be known in advance to make a connection.</p>
Access	<p>WAN : It works only in router mode. If the AP access to WAN only, the wireless client could get internet access from the AP, but could not see the other clients who are at LAN.</p> <p>LAN+WAN : It works in router and AP mode. If the AP access to LAN+WAN, the wireless client could not only get</p>

	internet access from the AP, but also could see the other clients who are at LAN.
Active Client List	The function will show all connected clients.

Here is an example for Multiple AP function:

1. Please enable the AP1, and set Band as 2.4GHz (B+G+N).
2. Then please set the SSID as N.MINI, and please set the Access as LAN+WAN.

No.	Enable	Band	SSID	Data Rate	Broadcast SSID	WMM	Access	Active Client List
AP1	<input checked="" type="checkbox"/>	2.4 GHz (B+G+N) ▾	N.MINI	Auto ▾	Enabled ▾	Enabled ▾	LAN+WAN ▾	Show
AP2	<input type="checkbox"/>	2.4 GHz (B+G+N) ▾	airlive2	Auto ▾	Enabled ▾	Enabled ▾	LAN+WAN ▾	Show
AP3	<input type="checkbox"/>	2.4 GHz (B+G+N) ▾	airlive3	Auto ▾	Enabled ▾	Enabled ▾	LAN+WAN ▾	Show
AP4	<input type="checkbox"/>	2.4 GHz (B+G+N) ▾	airlive4	Auto ▾	Enabled ▾	Enabled ▾	LAN+WAN ▾	Show

3. Please click Apply Change button, and reboot N.MINI to make the setting effective.