

Q: Could I somehow create a profile on the FTP settings which will upload a jpg or any type of image every a specific time of period

A:

1.) Please upgrade the firmware 5.0.2.5152 or above.

5.0.2.5152 fimware download link:

http://69.64.87.53/airlive_fileserver/uploads/Firmware/IPCam_Series_5.0.2.5152_2010-1230.zip

2.) Set Video function.

a. Click on include Date & include Time.

b. Click on Include Text & enter the word you want.

The screenshot shows the 'Video Profile' configuration page of an IP camera. On the left is a navigation menu with 'Video' selected. The main content area has three tabs: 'Common', 'Video Profile', and 'ROI'. Under 'Text Overlay Setting', there are three checked options: 'Include Date' (with a predefined format of 'YYYY-MM-DD'), 'Include Time' (with a predefined format of '24h'), and 'Include Text' (with the text 'AirLive' entered). Below this is the 'Video Profile' section with 'MEGA Mode' selected over 'VGA Mode'.

3.) Set FTP Server

The screenshot shows a web interface for configuring an FTP Server. On the left is a sidebar with 'Live View' and various menu items, with 'Event Server' highlighted. The main content area has tabs for 'FTP Server', 'TCP Server', 'HTTP Server', and 'SAMBA Server'. Below the tabs is a table with one entry:

Name	FTP Server	FTP Port	FTP Path
1	ftp.airlive.com	21	

Below the table are form fields for configuring the selected FTP server:

- Name: (< 21 Digits)
- FTP Server: (< 64 Digits) [Test]
- FTP Login Name: (< 21 Digits)
- FTP Login Password: (< 21 Digits)
- FTP Port: 21 (1 ~ 65535)
- FTP Path: (< 64 Digits)
- FTP Passive Mode: Disable Enable

4.) Set Even Schedule

- set type: click on Schedule Trigger
- Set Action, click on Send FTP.

The screenshot shows the 'Event Schedule' configuration page. The sidebar has 'Event Schedule' highlighted. The main content area has tabs for 'Setting' and 'Record'. Below the tabs is a table with one entry:

Name	Enable	Type	Weekday	Start	Duration	Trigger by Prefix	Action
test	yes	Schedule	111111	0:0	24:0	x,x	FTP

Below the table are form fields for configuring the selected event schedule:

- Name: test
- Enable: Yes No
- Type: Event Trigger Schedule Trigger, Interval 60 (Seconds)
- Enable Time: Sun Mon Tue Wed Thu Fri Sat
Start from 0:0, Duration 24:0 ((max 168:00 hours))
- Trigger by: Sensor Active Motion Area
- Record File Prefix: (0 ~ 20 Digits)
- Action: Go Preset Tour
 Voice Alert, Duration (Seconds)
 Alarm Out, Duration (Seconds)
 Send FTP 1
 Send TCP
 Send HTTP
 Send E-Mail

Buttons: Add, Modify, Delete

5.) Set Record

- Set Record File Type: click on JPEG.
- Set Record File Prefix: enter the word you want.

c. Set JPEG Picture Number : One.

The screenshot shows a web interface with a sidebar on the left and a main content area on the right. The sidebar is titled 'Live View' and contains several menu items: Network, Camera, System, Video, Audio, User, E-Mail, Motion Detection, Event Server, and Event Schedule. The main content area has two tabs: 'Setting' and 'Record'. The 'Record' tab is selected. Below the tabs, there are three settings:

- Record File Type:** A radio button is selected for 'JPEG'. Other options are 'AVI - JPEG' and 'AVI - H264'.
- Record File Prefix:** A text input field contains the value 'airlive'. To the right of the field, it says '(0 ~ 20 Digits)'.
- JPEG Picture Numbers:** A radio button is selected for 'One'. The other option is 'Auto'.

6.) Results

