

Q: How to reset WMU-6500FS to factory default setting ?

A: 1. Please remove the HDD from WMU-6500FS.

2. Please connect WMU-6500FS to PC, and power on WMU-6500FS.

You have to wait a minute until WMU-6500FS boot up

When WMU-6500FS is boot up, the LED of Power is on, the LEDs of WLAN, LAN, Status/Backup are blinking.

3. Please press the "Shutdown" and "Backup" buttons simultaneously for 6 seconds to reset the system setting to factory default.

4. After releasing, the LEDs of HDD Status, USB1 ,USB2 ,Status/Backup are blinking 2 seconds, then off and on again.

If not, please repeat step2 and step3 again.

5. Then WMU-6500FS will reboot automatically.