



Gigabit RJ45 and SFP Fiber Converter

MC-1000SFP



Extends network connection

MC-1000SFP gigabit media converter allow users to extend communications distance with Gigabit performance via fiber optic cable. The MC-1000SFP provides media conversion between 100/1000Base-T and gigabit Fiber via various SFP transceiver.



Compact size converter

The Compact Size MC-1000SFP has a standalone design with plug-and-play for easy installation and save space.

Headquarter



Office 1

MC-1000SFP

Office 2

MC-1000SFP

SNMP-24MGB Plus

Specifications

AirLive MC-1000SFP

| | |
|--|---|
| Standard <ul style="list-style-type: none"> •IEEE 802.3 10Base-T •IEEE 802.3u 100Base-TX •IEEE 802.3ab 1000Base-T •IEEE 802.3z 1000Base-X | External Power Adapter <ul style="list-style-type: none"> •5V / 1A |
| Port <ul style="list-style-type: none"> •1* 10/100/1000Mbps Gigabit copper port <ul style="list-style-type: none"> - Auto-negotiation, auto-MDI/MDI-X support •1* 100/1000Mbps Gigabit fiber SFP port <ul style="list-style-type: none"> - SFP supports standard SFP fiber transceiver installation | Operating Temperature <ul style="list-style-type: none"> •0° ~ 50°C |
| Packet Buffer <ul style="list-style-type: none"> •1 | Jumbo Frame <ul style="list-style-type: none"> •9k |
| MAC Address <ul style="list-style-type: none"> •4K | Humidity <ul style="list-style-type: none"> •10% ~ 90% (non-condensing) |
| | LED <ul style="list-style-type: none"> •PWR (Power) <ul style="list-style-type: none"> - Green <ul style="list-style-type: none"> - Solid:Power is on - Off:Power is off |
| | Dimensions <ul style="list-style-type: none"> •30 × 110 × 140 mm |

Ordering Information:

AirLive MC-1000SFP Gigabit RJ45 and SFP Fiber Converter