

ACC-Joystick-NVR

USB Joystick Control Panel for AirLive CoreNVR

- Metal Housing
- 3-Axis Precision Movement
- Standard USB Interface
- 12 Programmable Keys



AirLive ACC-Joystick-NVR is an accessory for controlling PTZ cameras on AirLive CoreNVR series. It features 3-Axis auto coordinate orientation with precision movement, standard USB interface and 12 programmable keys which allows user to re-define the function of each button on configuration page of CoreNVR. Those functions are able to fully controls of PTZ movement and also some friendly controls on CoreNVR such as full screen switch, channel and division switch. You will find how easy to control both CoreNVR and PTZ camera with this accessory.

Joystick for PTZ Camera Control



SD-2020



Monitor

CoreNVR 9 /16



ACC-Joystick-NVR

Specifications

Model

- ACC-Joystick-NVR

Material

- Metal housing

Deflection

- X axis : $\pm 25^{\circ} \sim 30^{\circ}$; Y axis : $\pm 25^{\circ} \sim 30^{\circ}$; Z axis : $\pm 45^{\circ}$

Centering

- 3 axis auto coordinate orientation

Controlling interface

- USB 1.1

Function buttons

- 12 programmable keys

Storage Temperature

- $-20^{\circ}\text{C} \sim 70^{\circ}\text{C}$

Operation Temperature

- $0 \sim 50^{\circ}\text{C}$

Dimension

- 16 x 9.3 x 18 cm

Weight

- 820g

Ordering Information:

AirLive ACC-Joystick-NVR USB Joystick Control Panel for AirLive CoreNVR